



440 N. Wolfe Rd.
Sunnyvale, CA 94085
Email: sales@liftians.com
Tel: 408-771-6628
WEB: www.liftians.com

1: Sending a display

Send command (The Feed):

<http://192.168.1.20:8089/device/macnte/send?station=1&id=3&num=23&type=1&color=2>

Parameters:

1. Station: Pick Station Group ID
2. ID: eTag ID (1-8)
3. num: display number (0-255)
4. type: light display type (1:solid; 2: slow flash; 3: medium flash; 4: fast flash)
5. color: push button color (1:R; 2:G; 3:B; 4:RG; 5:GB; 6:RB; 7: RGB)

2: Closing one light

<http://192.168.1.20:8089/device/macnte/close?station=1&id=2>

3: Closing all lights

<http://192.168.1.20:8089/device/macnte/close?station=1>

4: Initializing the station

<http://192.168.1.20:8089/device/macnte/ins?station=1>

5: Resetting one light

<http://192.168.1.20:8089/device/macnte/ins?station=1&id=2>

This is used to reset a display after the picker pushes the button (product picked into the tote)



440 N. Wolfe Rd.
Sunnyvale, CA 94085
Email: sales@liftians.com
Tel: 408-771-6628
WEB: www.liftians.com

6: Return results

Result

```
{  
  "label": {  
    "id": "",  
    "num": 78,  
    "type": 1,  
    "color": 2  
  },  
  "result": "success"  
}
```